

OWNER'S MANUAL

LG Gaming Monitor (LED MONITOR*)

* LG LED Monitor applies LCD screen with LED backlights.

Please read this manual carefully before operating your set and retain it for future reference.

32GK650F

TABLE OF CONTENTS

LICENSE3	USING THE MONITOR	2 [·]
ASSEMBLING AND PREPARING 4 - Product Composition	- Connecting to a PC HDMI Connection DisplayPort Connection - Connecting AV Devices HDMI Connection - Connecting Peripherals Connecting Headphones	2
- Moving and Lifting the Monitor8 - Installing the Monitor10	USER SETTINGS	24
Assembling the Stand Installing on a Table Adjusting the Stand Height	- Activating the Main Menu Main Menu Features - User Settings	
Adjusting the Angle Pivot Feature	Menu Settings TROUBLESHOOTING	
Tidying up Cables Using the Kensington Lock Detaching the Stand Body Installing the Wall Mount Plate Installing on the Wall	PRODUCT SPECIFICATION - Factory Support Mode HDMI Timing (Video)	3 !

LICENSE

Each model has different licenses. Visit www.lg.com for more information on the license.



The terms HDMI and HDMI High-Definition Multimedia Interface, and the HDMI Logo are trademarks or registered trademarks of HDMI Licensing Administrator, Inc. in the United States and other countries.

ASSEMBLING AND PREPARING

Product Composition

Please check whether all the components are included in the box before using the product. If there are any missing components, contact the retailer where you purchased the product. Note that the product and related components may look different from those shown here.



CD (Owner's Manual / Software / Guides) / Cards (Depending on the country)



Power cord AC/DC Adapter (Depending on the country)



DisplayPort Cable
(Depending on the country)



Stand Base



Cable Holder



Stand Body



Mouse Holder



- Always use genuine LG components to ensure safety and product performance.
- The product warranty will not cover damage or injury caused by the use of unauthorized components.
- It is recommend that use the supplied components.
- If you use generic cables not certified by LG, the screen may not display or there
 may be image noises.



NOTE

- The components may look different from those illustrated here.
- Without prior notice, all product information and specifications contained in this
 manual are subject to change to improve the performance of the product.
- To purchase optional accessories, visit an electronics store or an online shopping site, or contact the retailer from which you purchased the product.
- · The power cord provided may differ depending upon the region.


Supported Drivers and Software

Check the drivers and software supported by your product and refer to the manuals on the CD enclosed in the product package.

Drivers and Software	Installation Priority	32GK650F	
Monitor Driver	Recommended	0	
OnScreen Control	Recommended	0	

- Required and Recommended: You can download and install the latest version from the enclosed CD or from the LGE website (www.lg.com).
- The monitor FW can be updated through the OnScreen Control.

Product and Button Description



How to Use the Joystick Button

You can easily control the functions of the monitor by pressing the joystick button or moving it left/right with your finger.


Basic Functions

	▼	Power on	Press the joystick button once with your finger to turn on the monitor.
		Power off	Press and hold the joystick button once with your finger to turn off the monitor.
		Volume control	You can control the volume by moving the joystick button left/right.
		Controls screen brightness	You can control the screen's brightness by moving the joystick button up/down.



 \bullet The joystick button is located at the bottom of the monitor.


Input Connector



Moving and Lifting the Monitor

When moving or lifting the monitor, follow these instructions to prevent the monitor from being scratched or damaged and to ensure safe transportation, regardless of its shape or size.

- Place the monitor in the original box or packing material before attempting to move it.
- Before moving or lifting the monitor, disconnect the power cord and all other cables.
- Hold the bottom and side of the monitor frame firmly. Do not hold the panel itself.





- When holding the monitor, the screen should face away from you to prevent it from being scratched.
- When transporting the monitor, do not expose the monitor to shock or excessive vibration.
- When moving the monitor, keep it upright and never turn the monitor on its side or tilt it sideways.




CAUTION

- · Avoid touching the monitor screen as much as possible.
 - This may result in damage to the screen or some of the pixels used to create images.




If you use the monitor panel without the stand base, its joystick button may cause
the monitor to become unstable and fall, resulting in damage to the monitor or
human injury. In addition, this may cause the joystick button to malfunction.




Installing the Monitor

Assembling the Stand


1



2










• Press the stand until the button reaches the top.







- Illustrations in this document represent typical procedures, so they may look different from the actual product.
- Do not apply foreign substances (oils, lubricants, etc.) to the screw parts when assembling the product. (Doing so may damage the product.)
- Applying excessive force when tightening screws may cause damage to the monitor. Damage caused in this way will not be covered by the product warranty.
- Do not carry the monitor upside down by just holding the base. This may cause the monitor to fall off the stand and could result in personal injury.
- When lifting or moving the monitor, do not touch the monitor screen. The force applied to the monitor screen may cause damage to it.

Installing on a Table

1 Lift the monitor and place it on the table in an upright position. Place the monitor at least 100 mm (3.94 inches) away from the wall to ensure sufficient ventilation.



2 Connect the power adapter to the monitor and then plug the power cord into the wall outlet.




3 Press the joystick button on the bottom of the monitor to turn on the monitor.



 Unplug the power cord before moving or installing the monitor. There is risk of electric shock.

Cautions When Connecting Power Cord




- Make sure to use the power cord that is provided in the product package and connect it to a grounded power outlet.
- If you need another power cord, please contact your local dealer or the nearest retail store.

Adjusting the Stand Height


- Place the monitor mounted on the stand base in an upright position.
- 2 Handle the monitor with both hands for safety.



Max. 110.0 mm (4.3 inches)








 When adjusting the screen height, do not place your hand on the stand body to avoid injury to your fingers.

Adjusting the Angle

- 1 Place the monitor mounted on the stand base in an upright position.
- 2 Adjust the angle of the screen.

The angle of the screen can be adjusted forward or backward from -5° to 15° for a comfortable viewing experience.





To avoid injury to the fingers when adjusting the screen, do not hold the lower part
of the monitor's frame as illustrated below.








 Be careful not to touch or press the screen area when adjusting the angle of the monitor.




NOTE



Swivel (counter clockwise 20°)

Pivot Feature

The pivot feature allows the monitor to rotate 90° clockwise.






WARNING

- To avoid scratching the stand base, make sure that when rotating the monitor using the pivot feature, the stand does not make contact with the monitor.
- 1 Raise the monitor to the maximum height.



2 Adjust the angle of the monitor in the direction of the arrow as shown in the figure.



3 Rotate the monitor clockwise as shown in the figure.



4 Complete the installation by rotating the monitor 90° as shown below.







NOTE

- Auto Pivot feature of the display is not supported.
- The screen can be rotated easily using the screen pivot shortcut key provided with your Windows operating system. Note that some Windows versions and some graphics card drivers may use different settings for the screen pivot key or may not support the pivot key at all.

Tidying up Cables

Arrange the cables using the cable holder as shown in the illustration.






Using the Kensington Lock

The connector for the Kensington security system is located at the bottom of the monitor.

For more information on installation and usage, refer to the Kensington lock owner's manual or visit the website at http://www.kensington.com.

Connect the monitor to a table using the Kensington security system cable.






 The Kensington security system is optional. You can obtain optional accessories from most electronics stores.

Detaching the Stand Body

- 1 Place the monitor's screen face down. To protect the screen from scratches, cover the surface with a soft cloth.
- 2 Remove the stand from the monitor by pressing the button on the bottom center of the back of the monitor.



Installing the Wall Mount Plate

This monitor meets the specifications for the wall mount plate or other compatible devices.

- 1 Place the screen face down. To protect the monitor panel (screen), cover the surface with a soft cloth or the monitor protection pad included in the product package.
- 2 Remove the four screws tightened on the back of the monitor.
- 3 Place the wall mount plate onto the monitor and align it with the screw holes.
- 4 Tighten the four screws using a screwdriver to fix the plate to the monitor.




NOTE

- · The wall mount plate is sold separately.
- For more information on installation, refer to the wall mount plate's installation quide.
- Be careful not to apply too much force while mounting the wall mount plate as it may cause damage to the screen.

Installing on the Wall

Install the monitor at least 100 mm (3.94 inches) away from the wall and leave about 100 mm (3.94 inches) of space at each side of the monitor to ensure sufficient ventilation. Detailed installation instructions can be obtained from your local retail store. Alternatively, please refer to the manual for how to install and set up a tilting wall mounting bracket.



To install the monitor to a wall, attach a wall mounting bracket (optional) to the back of the monitor.

Make sure that the wall mounting bracket is securely fixed to the monitor and to the wall.

- 1 If you use screws longer than the standard length, it may damage the inside of the product.
- 2 A non-VESA standard screw may damage the product and cause the monitor to fall. LG Electronics is not liable for any accidents relating to the use of nonstandard screws.

Wall Mount (mm)	100 x 100
Standard screw	M4 x L10
Number of screws	4
Wall Mount Plate (Optional)	RW120




- · Use the screws specified by VESA standards.
- The wall mount kit includes the installation guide and all necessary parts.
- The wall mounting bracket is optional. You can obtain optional accessories from your local dealer.
- The length of the screw may differ for each wall mounting bracket. Be sure to use the proper length.
- For more information, please refer to the user manual for the wall mounting bracket.



CAUTION

- Unplug the power cord before moving or installing the monitor to avoid electric shock.
- Installing the monitor on the ceiling or on a slanted wall may result in the monitor falling off, which could lead to injury. Use an authorized LG wall mount and contact the local dealer or qualified personnel.
- Applying excessive force when tightening screws may cause damage to the monitor. Damage caused in this way will not be covered by the product warranty.

- Use the wall mounting bracket and screws that conform to VESA standards.
 Damage caused by the use or misuse of inappropriate components will not be covered by the product warranty.
- When measured from the back of the monitor, the length of each installed screw must be 8 mm (0.3 inches) or less.



USING THE MONITOR

 The following instructions are based on the 32GK650F model. Illustrations in this manual may differ from the actual product.

Press the joystick button, go to **Settings** \rightarrow **Input**, and then select the input option.



CAUTION

- Do not press the screen for a prolonged time. This may cause image distortion.
- Do not display a still image on the screen for a prolonged time. This may cause image retention. Use a screensaver if possible.



NOTE


- When connecting the power cord to the outlet, use a grounded (3-hole) power strip or a grounded power outlet.
- The monitor may flicker when turned on in an area where the temperature is low.
 This is normal
- · Sometimes red, green, or blue spots may appear on the screen. This is normal.

Connecting to a PC

- · This monitor supports the *Plug and Play feature.
- * Plug and Play: A feature that allows you to add a device to your computer without having to reconfigure anything or install any manual drivers.

HDMI Connection

Transmits digital video and audio signals from your PC to the monitor. Connect your PC to the monitor using the HDMI cable as shown in the illustration below.




! CAUTION

- Using a DVI to HDMI / DP (DisplayPort) to HDMI cable may cause compatibility issues.
- Use a certified cable with the HDMI logo attached. If you do not use a certified HDMI cable, the screen may not display or a connection error may occur.
- · Recommended HDMI cable types
- High-Speed HDMI®/TM cable
- High-Speed HDMI®/TM cable with Ethernet

DisplayPort Connection

Transmits digital video and audio signals from your PC to the monitor. Connect the monitor to your PC using the DisplayPort cable as shown in the illustration below.






NOTE

- There may be no video or audio output depending on the DP (DisplayPort) version of the PC.
- Make sure to use the supplied DisplayPort cable of the product. Otherwise, this
 may cause the device to malfunction.

Connecting AV Devices

HDMI Connection

HDMI transmits digital video and audio signals from your AV device to the monitor. Connect your AV device to the monitor using the HDMI cable as shown in the illustration below






- Using a DVI to HDMI / DP (DisplayPort) to HDMI cable may cause compatibility issues.
- Use a certified cable with the HDMI logo attached. If you do not use a certified HDMI cable, the screen may not display or a connection error may occur.
- Recommended HDMI cable types
 - High-Speed HDMI®/TM cable
 - High-Speed HDMI®/TM cable with Ethernet

Connecting Peripherals

Connecting Headphones

Connect peripherals to the monitor via the headphones port. Connect as illustrated.





NOTE

- Peripheral devices are sold separately.
- If you use angled earphones, it may cause a problem with connecting another external device to the monitor. Therefore, it is recommended to use straight earphones.





Angled


Straight

• Depending on the audio settings of the PC and external device, headphones and speaker functions may be limited.

USER SETTINGS

Activating the Main Menu

- 1 Press the joystick button on the bottom of the monitor.
- 2 Move the joystick up/down (▲ / ▼) and left/right (◀ / ▶) to set the options.
- 3 Press the joystick button once more to exit the main menu.



Button		Menu Status	Description
	Main m	enu disabled	Enables the main menu.
	Main m	enu enabled	Exits the main menu. (Holding down the button to turn off the monitor. You can turn off the monitor this way at any time, including when the OSD is on.)
		Main menu disabled	Adjusts the monitor volume level.
		Main menu enabled	Enters the Input features.
	•	Main menu disabled	Adjusts the monitor volume level.
		Main menu enabled	Enters the Settings feature.
		Main menu disabled	Adjusts the monitor brightness level.
		Main menu enabled	Turns off the monitor.
		Main menu disabled	Adjusts the monitor brightness level.
	V	Main menu enabled	Enters the Game Mode feature.

Main Menu Features



Main Menu	Description		
Input	ets input mode.		
Power Off	erns off the monitor.		
Settings	Configures the screen settings.		
Game Mode	Sets the game mode for gaming.		
Exit	Exits the main menu.		

User Settings

Menu Settings

- 1 To view the settings menu, press the joystick button at the bottom of the monitor and then enter the **Settings**.
- 2 Configure the options by moving the joystick up/down/left/right.
- 3 To return to the upper settings or set other settings items, move the joystick to ◀ or press (憑).
- 4 If you want to exit the settings menu, move the joystick to ◀ until you exit.











Game Mode

Game Adjust

Picture Adjust

Input

General

Set	tings	Description	
Game Mode		Changes the game mode to the one optimized for a given feature.	
Game Adjust		Adjusts the 1ms Motion Blur Reduction, FreeSync, Black Stabilizer, Response Time, Cross Hair and Game Reset.	
Picture Adjust		Adjusts the Brightness, Contrast, Sharpness, Gamma, Color Temp, R/G/B, Black Level, DFC and Picture Reset.	
Input	Input List Selects the input mode.		
Aspect Ratio Adjusts the aspect ratio of the screen.		Adjusts the aspect ratio of the screen.	
General		Sets Language, SMART ENERGY SAVING, Power LED, Automatic Standby, HDMI Compatibility Mode, DisplayPort 1.2, OSD Lock, Information and Reset.	



• Your monitor's OSD (On Screen Display) may differ slightly from that shown in this manual.

Settings > Game Mode		Description
	Gamer 1	In this mode, users can customize elements including game-related options.
Gamer 2		Gamer 1 and Gamer 2 picture modes allow you to save two sets of customized display settings, including game-related setup options.
Game Mode	FPS	This mode is optimized for FPS games.It is suitable for very dark FPS games.
RTS		This mode is optimized for RTS Game.
	Optimizes the screen for viewing documents. You can brighten the screen in the settings menu.	

Settings > Game Adjust		Description		
		On	This mode minimizes motion blur in fast-moving videos. To take full advantage of this function, select 2560 x 1440 @ 120Hz/144Hz before enabling 1ms Motion Blur Reduction . This function is available for the following vertical frequency. (120Hz,144Hz)	
Game Adjust	1ms Motion Blur Reduction	Off	Turns 1ms Motion Blur Reduction Mode off.	
		NOTE To reduce mot	ion blur, brightness is reduced with backlight control.	
			Blur Reduction and FreeSync feature can not used at the same time.	
		This function is game-optimized.		
		It is recomme	nded to turn off when you are not using the gaming function.	

FreeSync Game Adjust		Supported Gr Supported Ve For more info	N erface: DisplayPort,HDMI. aphic Card : A graphic card that supports AMD's FreeSync is necessary. rsion : Make sure to update the graphic card to the latest driver. rmation and requirement, refer to AMD website at http://www.amd.com/FreeSync 1ms Motion Blur Reduction cannot be enabled simultaneously.
		Extended	Enable wider frequency range of FreeSync function than basic mode. The screen may flicker during the game play.
		Basic	Enable basic frequency range of FreeSync function.
		Off	FreeSync function off.
	Black Stabilizer	You can easily distinguish objects on dark game screens.	

		Sets a response time for displayed pictures based on the speed of the screen. For a normal environment, it is recommended that you use Fast . For a fast-moving picture, it is recommended that you use Faster . Setting to Faster may cause image sticking.			
	Response Time	Faster	Sets the response time to Faster.		
Game Adjust		Fast	Sets the response time to Fast.		
		Normal	Sets the response time to Normal.		
		Off	Does not use the response time improvement feature.		
	Cross Hair		Cross hair provides a mark on the center of the screen for First Person Shooter (FPS) games. Users can select the cross hair that fits their gaming environment among four different cross hairs.		
		When the monitor is off or enters energy saving mode, the cross hair feature is automatically turned off.			
	Game Reset	Returns game to the default settings.			

Settings > Picture Adjust			Description		
	Brightness	Adjusts the bright	tness of the screen.		
	Contrast	Adjusts the contr	ast of the screen.		
	Sharpness	Adjusts the sharp	ness of the screen.		
	Gamma	Mode 1, Mode 2, Mode 3	The higher the gamma value, the darker the image becomes. Likewise, the lower the gamma value, the lighter the image becomes.		
		Mode 4	If you do not need to adjust the gamma settings, select Mode 4.		
	Color Temp	Custom	The user can adjust it to red, green, or blue by customization.		
		Warm	Sets the screen color to a reddish tone.		
Picture Adjust		Medium	Sets the screen color to between a red and blue tone.		
		Cool	Sets the screen color to a bluish tone.		
	R/G/B	You can customiz	te the picture color using Red, Green , and Blue colors.		
	Black Level		evel (for HDMI only). Ference for a video signal, this is the darkest color the monitor can display.		
		High	Keeps the current contrast ratio of the screen.		
		Low	Lowers the black levels and raises the white levels from the current contrast ratio of the screen.		
	DFC	On	Adjusts the brightness automatically according to the screen.		
		Off	Disables the DFC feature.		
	Picture Reset	Returns picture a	nd color to the default settings.		

Settings > Input		Description		
	Input List	Selects the input mode.		
	Aspect Ratio	Adjusts the aspect ratio of the screen.		
Input		Full Wide	Displays the video in widescreen, regardless of the video signal input.	
		Original	Displays video according to the aspect ratio of the video signal input.	
		1:1	The aspect ratio is not adjusted from the original.	
		1440)	me for Full Wide , Original , and 1:1 options at the recommended resolution. (2560 x eSync Mode. (Go to Picture → Game Adjust → FreeSync , to set from FreeSync Basic	

Settings > General		Description			
	Language	Sets the menu screen to the desired language.			
	SMART ENERGY	High	Saves energy using the high-efficiency SMART ENERGY SAVING feature.		
		Low	Saves energy using the low-efficiency SMART ENERGY SAVING feature.		
	SAVING	Off	Disables the SMART ENERGY SAVING feature.		
		Turns the power LED on the bottom of the monitor on or off.			
	Power LED	On	The power LED turns on automatically. On Mode: Red Sleep Mode: Flashing Red Off Mode: Off		
		Off	The power LED turns off.		
	Automatic Standby	Feature that automatically turns off the monitor when there is no movement on the screen for a period of time. You can set a timer for the auto-off function. (Off, 4H, 6H, and 8H)			
General		HDMI Compatibility Mode feature can recognize the legacy equipment that does not support HDMI 2.0.			
		On	Enables HDMI Compatibility Mode.		
		Off	Disables HDMI Compatibility Mode.		
	HDMI Compatibility	NOTE			
	Mode	 If the connected device does not support HDMI Compatibility Mode, the screen or sound may not work properly. When HDMI Compatibility Mode is on, 2560 x 1440 @ 120/144Hz resolution is not supported. 			
		Some older graphics cards do not support HDMI 2.0,but you can select HDMI 2.0 resolution in the control panel of window. This may cause the screen to appear abnormally.			
	DisplayPort 1.2	NOTE Be sure to	configure this option according to the DisplayPort version supported by your graphics card. Set this option to Disable hics card does not support DisplayPort 1.2.		

	OSD Lock	This feature disables the configuration and adjustment of menus.		
		On	Enables OSD Lock.	
		Off	Disables OSD Lock.	
General		⚠ NOTE		
		All features are disabled except Brightness, Contrast in Picture Adjust, Input, OSD Lock and Information in General.		
	Information	The display information will be shown the Model, Serial Number, Total Power On Time, Resolution.		
Reset Restores the default settings.		efault settings.		

TROUBLESHOOTING

Nothing is displayed on the screen.	
Is the monitor's power cord plugged in?	Check if the power cord is correctly plugged into the power outlet.
Is the power LED on?	Check the power cable connection and press the power button.
Is the power on and the power LED displaying red?	Check that the connected input is enabled (Settings > Input).
Is the power LED blinking?	If the monitor is in sleep mode, move the mouse, or press any key on the keyboard, to switch the display on. Check if the computer is turned on.
Is the The screen is not currently set to the recommended resolution. If you have no video or the screen flickers, see the troubleshooting guide in the product owner's manual. message being displayed?	This occurs when signals transferred from the PC (graphics card) are out of the recommended horizontal or vertical frequency range of the monitor. Please see the Product Specification section of this manual to set the appropriate frequency.
Is the No Signal message being displayed?	This is displayed when the signal cable between the PC and the monitor is missing or disconnected. Check the cable and reconnect it.
Have you installed the display driver?	 Be sure to install the display driver from the display driver CD (or diskette) that comes with your display. Or, you can also download the driver from our web site: http://www.lg.com. Make sure to check if the graphics card supports Plug and Play function.

Some features are disabled.			
Are some functions not available when	• The OSD is locked. Go to Settings > General and set OSD Lock to Off .		
you press the Menu button?			

The screen retains an image.			
Does image sticking occur even when the	Displaying a still image for a prolonged time may cause damage to the screen, resulting in the retention of the image.		
monitor is turned off?	To extend the lifetime of the monitor, use a screensaver.		

Screen display is unstable and shaky. / Images displayed on the monitor leave shadow trails.			
Did you select the appropriate resolution?	If the selected resolution is HDMI 1080i 60/50 Hz (interlaced), the screen may be flickering. Change the resolution to 1080p or the recommended resolution.		



NOTE

- Vertical Frequency: In order to display an image, the screen must be refreshed dozens of times per second, like a fluorescent lamp. The number of times the screen is refreshed per second is called vertical frequency, or refresh rate, and is represented by Hz.
- Horizontal Frequency: The time it takes to display one horizontal line is called the horizontal cycle. If 1 is divided by the horizontal interval, the result is the number of horizontal lines displayed per second. This is called horizontal frequency and is represented by kHz.
- Check if the graphics card's resolution or frequency is within the range allowed by the monitor and set it to the recommended (optimal) resolution **Control Panel** > **Display** > **Settings** in Windows. (The settings may differ depending on the operating system (OS) you use.)
- Not setting the graphics card to the recommended (optimal) resolution may result in blurred text, a dimmed screen, a truncated display area or misalignment of the display.
- The setting methods may be different depending on the computer or operating system, and some resolutions may not be available depending on the performance of the graphics card. If this is the case, contact the manufacturer of the computer or graphics card for assistance.
- Some graphics cards may not support 2560 x 1440 resolution. If the resolution cannot be displayed, contact the manufacturer of your graphics card.

The display color is abnormal.			
Does the display appear discolored (16 colors)?	• Set the color to 24 bit (true color) or higher. In Windows, go to Control Panel > Display > Settings > Color Quality . (The settings may differ depending on the operating system (OS) you use.)		
Does the display color appear unstable or monochrome?	Check if the signal cable is connected properly. Reconnect the cable or reinsert the PC's graphics card.		
Are there spots on the screen?	When using the monitor, pixilated spots (red, green, blue, white, or black) may appear on the screen. This is normal for an LCD screen. It is not an error, nor is it related to the monitor's performance.		

No sound from the headphone port.				
Are images displayed using DP (DisplayPort) or HDMl input without sound?	 Make sure that the headphone port connections are made properly. Try increasing the volume with the joystick. Set the audio output of the PC to the monitor you are using. On Microsoft Windows, go to Control Panel > Hardware and Sound > Sound > set the Monitor as default device. (The settings may differ depending on the operating system (OS) you use.) 			

PRODUCT SPECIFICATION

LCD Screen	Time		TET (Thin Film Transistor)	
LCD Screen	Туре		TFT (Thin Film Transistor)	
			LCD (Liquid Crystal Display) Screen	
	Color Depth		HDMI	8-bit color is supported.
			DP (DisplayPort)	8-bit color is supported.
	Pixel Pitch		0.2724 mm x 0.2724 mm	
Resolution	Max Resolutio	n	2560 x 1440 @ 144 Hz	
	Recommended Resolution		2560 x 1440 @ 60 Hz	
Operating Frequency	HDMI	Horizontal Frequency	30 kHz to 230 kHz	
		Vertical Frequency	50 Hz to 144 Hz	
	DP	Horizontal Frequency	30 kHz to 230 kHz	
		Vertical Frequency	50 Hz to 144 Hz	
Input Connector	H/P ∩, DP (DisplayPort) IN, HDMI IN 1/2			
Power Sources	Power Rating		19 V 3.3 A or 19 V	 2.4 A
	Power Consumption		Operating Mode: 44 W (Typical)*	
	(Typical)		Sleep Mode: ≤ 0.5 W	
			Off Mode: ≤ 0.3 W	
AC/DC Adapter	DA-65G 19, manufactured by Asian Power Devices Inc.			
	LCAP39, manufactured by LIEN CHANG ELECTRONIC ENTERPRISE			
	Output: 19 V 3.42 A			
	DA-48F 19, manufactured by Asian Power Devices Inc.			
	Output: 19 V 2.53 A			

Environmental Conditions	Operating Conditions	Temperature	0 °C to 40 °C (32 °F to 104 °F)	
		Humidity	Less than 80 %	
	Storing Conditions	Temperature	-20 °C to 60 °C (-4 °F to 140 °F)	
		Humidity	Less than 85 %	
Dimensions	Monitor Size (Width x Height x Depth)			
	With Stand	715.2 x 493.9 x 272.2 (mm)		
		28.1 x 19.4 x 10.7 (inches)		
	Without Stand	715.2 x 423.9 x 57.1 (mm)		
		28.1 x 16.6 x 2.2 (inches)		
Weight (Without Packaging)	With Stand	8.3 kg (18.3 lbs)		
	Without Stand	6.5 kg (14.3 lbs)		

Specifications are subject to change without notice.

^{*} The Operating Mode of Power Consumption is measured with LGE test standard. (Full White pattern, Maximum resolution)

^{*} The Power Consumption level can be different by operating condition and monitor setting.

Factory Support Mode

(Preset Mode, HDMI/ DisplayPort PC)

Preset Mode	Horizontal Frequency (kHz)	Vertical Frequency (Hz)	Polarity (H/V)	Remarks
640 x 480	31.469	59.94	-/-	
800 x 600	37.879	60.317	+/+	
1024 x 768	48.363	60.0	-/-	
1152 x 864	54.347	60.05	+/+	
1280 x 720	45	60	+/+	
1280 x 1024	63.981	60.02	+/+	
1600 x 900	60.00	60.00	+/+	
1680 x 1050	65.29	59.954	-/+	
1920 x 1080	67.50	60	+/-	
1920 x 1080	83.894	74.973	+/-	
2560 x 1440	88.79	59.95	+/-	
2560 x 1440	111.86	74.97	+/-	
2560 x 1440	183.0	120.0	+/-	*
2560 x 1440	222.19	144.0	+/-	*

^{*} When HDMI Compatibility Mode is on, 2560 x 1440 @ 120/144Hz resolution is not supported.

HDMI Timing (Video)

Factory support mode (Preset Mode)	Horizontal Frequency (kHz)	Vertical Frequency (Hz)	Remarks
480p	31.5	60	
720p	45.0	60	
1080p	67.5	60	
2160p	135	60	When HDMI Compatibility Mode is set to OFF.



Declaration of Conformity

Trade Name: LG Model: 32GK650F

Responsible Party: LG Electronics Inc.

Address: 1000 Sylvan Ave. Englewood Cliffs NJ 07632 U.S.A

TEL: 201-266-2534

Read the owner's manual (CD) carefully and keep it at hand. Please note that the label attached to the product provides information for technical support.

Model ______Serial No. _____

To obtain the source code under GPL, LGPL, MPL, and other open source licenses, that is contained in this product, please visit http://opensource.lge.com.ln addition to the source code, all referred license terms, warranty disclaimers and copyright notices are available for download.LG Electronics will also provide open source code to you on CD-ROM for a charge covering the cost of performing such distribution (such as the cost of media, shipping, and handling) upon email request to opensource@lge.com. This offer is valid for three (3) years from the date on which you purchased the product.